  
**JV-1010**  
64-VOICE SYNTHESIZER  
MODULE

---

### It's a Fact...

The JV-1010 64-Voice Synthesizer Module is a half rackspace sound module that features the full sound set of the JV-1080/2080 synth modules. It also includes the sounds from the Session wave expansion board, and a slot for installing an additional SR-JV80 Series expansion board of your choice. Features include:

- Compact half-rackspace, expandable synth module with 64-voice polyphony
- Includes the complete sound set of the JV-1080/2080 sound modules, plus the sounds from the Session expansion board (1023 patches before expansion)
- Expansion slot for installing one of sixteen additional SR-JV80 Series Wave Expansion boards
- Intuitive knob-style control and straightforward interface
- Dedicated reverb and chorus effects, plus 40 built-in effect algorithms such as distortion and rotary simulation
- Phrase Preview button and Category Bank Select knob make it easy to find the patches you want
- General MIDI compatible
- Includes Emagic® SoundDiver™ software for patch editing

---

### Initialize

This function resets the settings of the patch, performance, and rhythm sets to the factory default settings. Use the following procedure to initialize the JV-1010:

1. Press VALUE knob to switch to a mode other than the patch mode.
2. Hold down the VOLUME knob and press the VALUE knob.
3. Turn the CATEGORY/BANK knob to select PIANO (Factory Reset).
4. Press the VALUE knob to display "Sur."
5. Press the VALUE knob to initialize the JV-1010.

# TurboStart

---

### Playing the Demo Songs

The JV-1010 contains four demo songs that demonstrate its internal sounds and effects. Use the following procedure to listen to the demo songs:

1. Turn the CATEGORY/BANK knob to select DEMO.
2. Turn the VALUE knob to select the desired song.
3. Press the VALUE knob or the VOLUME knob start demo song playback. Press either knob again to stop playback.

---

### Selecting Patches

The JV-1010 contains over 1,000 built-in sounds. Use the following procedure to select a patch:

1. Press the VALUE knob to select Patch mode (PATCH).
2. Turn the CATEGORY/BANK knob to select the desired bank.
3. Turn the VALUE knob to select the desired patch.

Try these patches:


- User: No. 017 Adrenaline
- Preset-A: No. 023 PsychoRhodes
- Preset-B: No. 052 Blade Racer
- Preset-E: No. 095 Dimensional
- Session: No. 182 DCO Sweeper.

---

### Using the Category Function

The Category function allows you to search for patches based on instrument type. Use the following procedure to select a patch by category:

1. Press the VALUE knob to select Patch mode (PATCH).
2. Turn the CATEGORY/BANK knob to select a category.
3. Turn the VALUE knob to select the desired patch.

 **JV-1010**  
64-VOICE SYNTHESIZER  
MODULE

# TurboStart

---

## Auditioning Patches (Phrase Preview)

The Phrase Preview function allows you to audition sounds at the touch of a button. A short sample of the selected patch is played in a style associated with that sound. Use the following procedure to try the Phrase Preview function:

1. Press the VALUE knob to select the Patch mode.
2. Turn the CATEGORY/BANK knob to select Session.
3. Turn the VALUE knob to select 023.
4. Hold down the VOLUME knob to hear the selected patch.

---

## Using the JV-1010 as a GM Module

The JV-1010 features a GM (General MIDI) mode that provides a convenient way to play back or create General MIDI-compatible files. Use the following procedure to place the JV-1010 into GM mode:

1. Press the VALUE knob repeatedly to select GM.

---

## Configuring the JV-1010 with SoundDiver

A copy of Emagic's SoundDiver is included for patch editing on the JV-1010. This software allows you to quickly and easily edit the parameters of the JV-1010 from your Mac or PC.

Before you can do this, it is necessary to configure the JV-1010 for use with your computer. First, you will need to connect the proper cable—for PC use RSC-15AT, for Mac use RSC-15APL—to the serial port on your computer. Or, if you already have a MIDI interface, connect the MIDI ports on the JV-1010 to your interface.

Make sure the power for the JV-1010, the computer, and any additional devices is turned off, and use the following procedures to configure the JV-1010 for use with SoundDiver.

### *For PC:*

1. Connect a RSC-15AT serial cable from the serial port of the JV-1010 to the computer's serial port (RS-232C).
2. Set the COMPUTER switch on the rear panel to PC-2.
3. Turn the power for all devices on.

### *For Mac:*

1. Connect a RSC-15APL serial cable from the serial port of the JV-1010 to the computer's serial port.
2. Set the COMPUTER switch on the rear panel to Mac.
3. Turn the power for all devices on.

### *Using MIDI:*

1. Set the COMPUTER switch on the rear panel to MIDI.
2. Connect a MIDI cable from the JV-1010's MIDI OUT to the MIDI IN of the MIDI interface.
3. Connect a MIDI cable from the JV-1010's MIDI IN to the MIDI OUT of the MIDI interface.
4. Turn the power for all devices on.